

## A520MH 3.0 Motherboard



- Supports AMD Ryzen™ 3rd Gen (Matisse/ Renoir) and Ryzen™ 4th Gen (Vermeer/ Cezanne) processors
- AMD A520 single chip architecture
- Supports 2-DIMM DDR4-4933+(OC)/4800(OC)/4600(OC)/4400(OC)/4000(OC)/3800(OC)/3600(OC)/3200/2933/2667/2400/2133/1866
- Supports USB 3.2 Gen1
- Supports PCIe M.2
- Supports HDMI 4K resolution

### Specification

|                  |   |
|------------------|---|
| CPU SUPPORT      | Socket AM4 support AMD Ryzen™ 3rd Gen (Matisse/ Renoir) and Ryzen™ 4th Gen (Vermeer/ Cezanne) processors<br>Support for future AMD Ryzen processors with BIOS update<br>* Please refer to <a href="http://www.biostar.com.tw">www.biostar.com.tw</a> for CPU support list.  |
| MEMORY           | 4th Gen AMD Ryzen Processors (Vermeer CPUs):<br>Supports Dual Channel DDR4 4400+(OC)/ 4000(OC)/ 3800(OC)/ 3600(OC)/ 3200/ 2933/ 2667/ 2400/ 2133<br>4th Gen AMD Ryzen with Radeon Graphics Processors (Cezanne APUs):<br>Supports Dual Channel DDR4 4933+(OC)/ 4800(OC)/ 4600(OC)/ 4400(OC)/ 4000(OC)/ 3800(OC)/3600(OC)/ 3200/ 2933/ 2667/ 2400/ 2133<br>3rd Gen AMD Ryzen Processors (Matisse CPUs):<br>Supports Dual Channel DDR4 4400+(OC)/ 4000(OC)/ 3800(OC)/ 3600(OC)/ 3200/ 2933/ 2667/ 2400/ 2133<br>3rd Gen AMD Ryzen with Radeon Graphics Processors (Renoir APUs):<br>Supports Dual Channel DDR4 4933+(OC)/ 4800(OC)/ 4600(OC)/ 4400(OC)/ 4000(OC)/ 3800(OC)/ 3600(OC)/ 3200/ 2933/ 2667/ 2400/ 2133<br>2 x DDR4 DIMM Memory Slot, Max. Supports up to 64 GB Memory<br>Each DIMM supports non-ECC 8/ 16/ 32 GB DDR4 module<br>* Please refer to <a href="http://www.biostar.com.tw">www.biostar.com.tw</a> for Memory support list. |
| INTEGRATED VIDEO | By CPU model<br>Supports DX12<br>Supports HDCP  |
| STORAGE          | Total supports 1x M.2 socket and 4 x SATA III (6Gb/s) ports<br>AMD Ryzen 5000/5000 G/4000 G/3000 Processors<br>1 x M.2 (M Key) Socket (M2_PCIEG3_32G_SATA):<br>Supports M.2 Type 2242/ 2260/ 2280 SSD module<br>Supports PCIe 3.0 x 4 (32Gb/s) & SATA III (6.0Gb/s) SSD<br>AMD A520 Chipset<br>4 x SATA III Connectors (6Gb/s) : Supports AHCI & RAID 0, 1, 10  |
| LAN              | Realtek RTL8111H<br>10/ 100/ 1000 Mb/s auto negotiation, Half / Full duplex capability  |

|                 |   |
|-----------------|---|
| AUDIO CODEC     | ALC897<br>7.1 Channels, High Definition Audio, Hi-Fi (Front)  |
| USB             | 6 x USB 3.2 (Gen1) ports (4 on rear I/Os and 2 via internal headers)<br>6 x USB 2.0 ports (2 on rear I/Os and 4 via internal headers)   |
| EXPANSION SLOT  | AMD Ryzen 5000/3000 Series Processors<br>1 x PCIe 3.0 x16 Slot(x16 or x4/x4/x4/x4 mode)<br>or<br>AMD Ryzen 5000 G/4000 G Series Processors<br>1 x PCIe 3.0 x16 Slot(x16 or x8/x4/x4 mode)<br>AMD A520 Chipset<br>2 x PCIe 3.0 x1 Slot<br>* According to different CPUs will have different speeds.  |
| REAR I/O        | 1 x PS/2 Keyboard<br>1 x PS/2 Mouse<br>1 x HDMI Port<br>1 x VGA Port<br>1 x LAN port<br>4 x USB 3.2 (Gen1) Ports<br>2 x USB 2.0 Ports<br>3 x Audio Jack   |
| INTERNAL I/O    | 4 x SATA III (6.0Gb/s) Connectors<br>2 x USB 2.0 Header (each header supports 2 USB 2.0 ports)<br>1 x USB 3.2 (Gen1) Header (each header supports 2 USB 3.2 (Gen1) ports)<br>1 x 8-Pin Power Connector<br>1 x 24-Pin Power Connector<br>1 x CPU Fan Connector<br>1 x System Fan Connector<br>1 x Front Panel Header<br>1 x Front Audio Header<br>1 x Internal Stereo Speaker Header<br>1 x Clear CMOS Header<br>1 x COM Port Header<br>1 x TPM Header |
| H/W MONITORING  | CPU / System Temperature Monitoring<br>CPU / System Fan Monitoring<br>Smart / Manual CPU Fan Control<br>CPU/DDR Voltage Monitoring  |
| DIMENSION       | Micro ATX Form Factor Dimension: 20.8cm x 24.4cm ( W x L )  |
| OS SUPPORT      | Supports Windows 10(64bit) / 11(64bit)<br>*Biostar reserves the right to add or remove support for any OS with or without notice  |
| BUNDLE SOFTWARE | BullGuard   |
| ACCESSORIES     | 2 x SATA Cable<br>1 x I/O Shield<br>1 x DVD Driver<br>1 x Quick Guide<br>1 x M.2 Anchor   |
| FEATURES        | Supports 100% Solid capacitor<br>BIO-FLASHER<br>A.I FAN<br>PCIe M.2 32Gb/s  |

## OVERVIEW

|   |  |
|---|--|
|    | <h3>AMD A520 chipset</h3> <p>AMD A520 chipset provides a simple, stable platform and more than enough connectivity and bandwidth options to satisfy both demanding home users and media aficionados.</p>   |
|    | <h3>HD Audio</h3> <p>Provides high quality sound with minimal loss of audio fidelity.</p>  |
|    | <h3>Hi-Fi Ground</h3> <p>BIOSTAR Hi-Fi Ground ( Golden Line ) is noise-blocking multi-layer PCB design to isolates analog audio signals from digital sources. Unique PCB layout is ideal for exceptional clarity and high fidelity sound.</p>  |
|    | <h3>HDMI 4K2K</h3> <p>The new 4K2K resolution enables high-definition image display with four times the resolution of full HD, 4K2K display is faithfully express bright, highly detailed content that fills the entire screen with lifelike images. Connectivity with PCs via a single HDMI cable for displaying 4K2K data.</p>                                 |
|   | <h3>DX12</h3> <p>DirectX 12 introduces the next version of Direct3D, the graphics API at the heart of DirectX. Direct3D is one of the most critical pieces of a game or game engine, and we've redesigned it to be faster and more efficient than ever before. Direct3D 12 enables richer scenes, more objects, and full utilization of modern GPU hardware.</p> |
|  | <h3>Integrated HDMI with HDCP</h3> <p>Onboard HDMI connector allows full video &amp; audio support. It has industry-leading high definition video quality.</p>   |
|  | <h3>PCIe M.2</h3> <p>PCIe M.2 32Gb/s delivers the highest bandwidth and lower latency. It is 3 times faster compared with PCIe M.2 10Gb/s.</p>   |
|  | <h3>PCIe 3.0</h3> <p>PCIe 3.0 is the ubiquitous and general-purpose PCI Express I/O standard. At 8GT/s bit rate, the interconnect performance bandwidth is doubled over PCIe 2.0, while preserving compatibility with software and mechanical interfaces.</p>  |
|  | <h3>SATAIII 6Gbps</h3> <p>SATAIII 6Gbps provides a higher bandwidth to retrieve and transfer HD media. With this super speed data transfer, SATAIII allows an incredible data boost which is 2x faster than the SATA II.</p>   |
|  | <h3>Dual DDR4</h3> <p>The primary advantages of DDR4 over DDR3, include higher module density, lower voltage requirements, coupled with higher data transfer rate.</p>   |

|   |   |
|---|---|
|     | <h3>USB 3.2 Gen1 Type-A</h3> <p>USB 3.2 Gen1 delivers a compelling performance boosts and can be used to connect multiple devices without worrying about compatibility. It is capable of data transfer speeds up to 5Gbps and backwards compatible with all existing USB products.</p>  |
|    | <h3>Super Durable Solid Caps</h3> <p>The best quality solid state capacitors with ultra low ESR design, the Super Durable Solid Caps doubles the lifespan.</p>  |
|    | <h3>Moistureproof PCB</h3> <p>The PCB will be oxidizing easily by damp or absorbed moisture, and ionic migration or CAF (Conductive Anodic Filament) will be generated. Moistureproof PCB meets high density and high reliability requirements for moisture proof.</p>  |
|    | <h3>Super LAN Surge Protection</h3> <p>Super LAN Surge Protection, providing LAN port with more advanced antistatic protection capabilities by adding an integrated chip to strengthen electrical stability and prevent damage from lightning strikes and electrical surges. SLSP (Super LAN Surge Protection) series motherboard upgrades the existing system protection standards with maximum 4X protection comparing to other board makers.</p>             |
|  | <h3>OC / OV / OH Protection</h3> <p>OC / OV / OH Protection design detects overvoltage conditions and prevents voltage surges from spreading in real time. It also actively cuts off the overvoltage supply to protect your system.</p>   |
|  | <h3>BullGuard Internet Security (90 days FREE trial)</h3> <p>BullGuard Internet Security comes with the broadest line-up of internet security features on the market, including: a cutting-edge dual Antivirus engine, Online Backup for your precious files, PC Tune Up to speed up your system, a Game Mode for a seamless gaming experience, Parental Control, Firewall, Safe Browsing and many more. Make the most of your digital life with Bullguard!</p> |
|  | <h3>UEFI BIOS</h3> <p>Unified Extensible Firmware Interface (UEFI) is a brand new framework that provides a revolutionary interface. It is a modern clear and easy-to-use graphical user interface. The UEFI comes with a colorful easy-understand icons leads users into the setup layer directly.</p>   |
|  | <h3>BIO-Flasher</h3> <p>BIO-Flasher is a convenient BIOS update tool. Just launch this tool and put the BIOS on USB pen driver before entering the OS. You can update your BIOS with only a few clicks without preparing an additional floppy disk or other complicated flash utility.</p>  |
|  | <h3>A.I FAN</h3> <p>With A.I FAN users can ensure that their gaming PC can maintain its performance while staying cool. According to different cooling needs and usage scenarios, users can control speed modes. Allows users to have more customizability of fan modes and automatically detects different temperatures to make fan operate at defined speed for optimal cooling performance.</p>  |





## Smart Update

Biostar Smart Update is a utility that can help users run online update. It can download the drivers for your motherboard from Biostar official website and install them automatically.



## HDMI

The terms HDMI and HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator, Inc. in the United States and other countries.

\*The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!



BIOSTAR®  
Beyond Better, Racing to the Future.